

PRODUCT-DETAILS

ESB25-30N-06

ESB25-30N-06 Installation Contactor (NO) 25 A - 3 NO - 0 NC - 230 ... 240 V - Control Circuit 400 Hz



General Information	
Extended Product Type	ESB25-30N-06
Product ID	1SAE231111M0630
Catalog Description	ESB25-30N-06 Installation Contactor (NO) 25 A - 3 NO - 0 NC - 230 240 V - Control Circuit 400 Hz
	The ESB25N installation contactors are used to control single and three-phase loads up to 25 A and can be operated by AC or DC. These contactors are made for use in household applications as well as in industrial
Long Description	environments. The following benefits are provided: Hum-free operation, low power consumption and integrated overvoltage protection.

 Ordering
 4013614519680

 Package Level 1 EAN
 4013614519680

 Minimum Order Quantity
 6 piece

 Customs Tariff Number
 85365080

Popular Downloads	
Data Sheet, Technical Information	2CDC103051C0201
Instructions and Manuals	2CDC103043M6801
CAD Dimensional Drawing	2CDC001079B0201

Various contact combinations and accessories are available.

ESB25-30N-06 2

Dimensions	
Product Net Width	36 mn
Product Net Height	85 mm
Product Net Depth / Length	65 mm
Product Net Weight	0.23 kc
Technical	
Rated Operational Voltage	Main Circuit 220 V DC Main Circuit 400 V AC
Rated Control Circuit Voltage (U _C)	230 240 V
Rated Frequency (f)	Control Circuit 400 Hz Control Circuit 50 Hz Control Circuit 60 Hz Control Circuit 60 Hz Main Circuit 50 Hz Main Circuit 60 Hz Main Circuit DC
Rated Operational Current AC-1 (I _e)	(NO) 25 A
Rated Operational Current AC-3 (I _e)	(230 V) Single Phase, NO 9 A (400 V) Three Phase, NO 9 A
Rated Operational Power AC-1 (P _e)	(230 V) Single Phase, NO 5.8 kW (400 V) Three Phase, NO 17.3 kW
Rated Operational Power AC-3 (P _e)	(230 V) Single Phase, NO 1.3 kW (400 V) Three Phase, NO 4 kW
Rated Operational Current AC-7a (I _e)	(NO) 25 A
Rated Operational Power AC-7a (P _e)	(230 V) Single Phase, NO 5.8 kW (400 V) Three Phase, NO 17.3 kW
Rated Operational Current AC-7b (I _e)	(230 V) Single Phase, NO 9 A (400 V) Three Phase, NO 9 A
Rated Operational Power AC-7b (P _e)	(230 V) Single Phase, NO 1.3 kW (400 V) Three Phase, NO 4 kW
Recommended Screw Driver	Control Circuit Pozidriv Main Circuit Pozidriv
Rated Impulse Withstand Voltage (U _{imp})	6 kV
Rated Insulation Voltage (U _i)	500 V
Connecting Capacity Main Circuit	Flexible with Ferrule 1x 1.5 10 mm Flexible with Ferrule 2x 1.5 2.5 mm Flexible with Insulated Ferrule 1x 1.5 10 mm Flexible with Insulated Ferrule 2x 1.5 mm Flexible 1x 1.5 10 mm Flexible 2x 1.5 4 mm Rigid 1x 1.5 4 mm
Connecting Capacity Control Circuit	Flexible with Ferrule 1x 1 2.5 mm Flexible with Ferrule 2x 0.75 1 mm Flexible with Insulated Ferrule 1x 1 2.5 mm Flexible with Insulated Ferrule 2x 0.75 1 mm Flexible 1x 1 4.0 mm Flexible 2x 1 2.5 mm Rigid 1x 1 4 mm Rigid 2x 1 2.5 mm
Tightening Torque	Control Circuit 0.9 N·m Main Circuit 1 N·m
Wire Stripping Length	Control Circuit 7 mm Main Circuit 10 mm
Degree of Protection	IP20
Electrical Durability	AC-1 (NO) 130000 cycle AC-3 (NO) 500000 cycle AC-7a (NO) 130000 cycle AC-7b (NO) 500000 cycle

ESB25-30N-06 3

Mechanical Durability	1000000 cycle
Number of Poles	3
Number of Auxiliary Contacts NC	0
Number of Auxiliary Contacts NO	0
Number of Main Contacts NC	0
Number of Main Contacts NO	3
Width in Number of Modular Spacings	2
Pollution Degree	3
Standards	IEC/EN 60947-1 IEC/EN 60947-4-1 IEC/EN 61095 UL 60947-1 UL 60947-4-1

Technical UL/CSA	
Maximum Operating Voltage UL/CSA	Main Circuit 480 V AC
Horsepower Rating UL/CSA	(220 240 V AC) Single Phase, NO 1 Hp (220 240 V AC) Three Phase, NO 3 Hp (440 480 V AC) Single Phase, NO 2 Hp (440 480 V AC) Three Phase, NO 5 Hp
Connecting Capacity Main Circuit UL/CSA	Solid 16-8 AWG Stranded 16-8 AWG
Connecting Capacity Control Circuit UL/CSA	Solid 16-10 AWG Stranded 16-10 AWG
Tightening Torque <u>UL/CSA</u>	Control Circuit 8 in·lb Main Circuit 9 in·lb

Environmental	
Ambient Air Temperature	Operation -25 +55 °C Storage -40 +80 °C
Maximum Operating Altitude Permissible	2000 m
Resistance to Shock acc. to IEC 60068-2-27	11 ms Pulse 15g
RoHS Status	Following EU Directive 2011/65/EU and Amendment 2015/863 July 22, 2019

ABS Certificate	1SAA920000-010 ⁻
CB Certificate	1SAA920004-200 ⁻
CQC Certificate	CQC2017010304993564 CQC2017010304993565
Declaration of Conformity - CCC	2020980304001312 2020980304001314
Declaration of Conformity - CE	1SAD938506-0302
Declaration of Conformity - UKCA	1SAD938501-1302
DNV Certificate	1SAA920000-0306
EAC Certificate	1SAA920001-2702
Environmental Information	1SAC200063H0009
Instructions and Manuals	2CDC103043M680 ⁻
REACH Declaration	2CMT2021-006202
RINA Certificate	1SAA920000-080 ⁻
RMRS Certificate	1SAA920000-0705
RoHS Information	2CMT2021-006277
UL Certificate	E191658-1996030

ESB25-30N-06 4

Container Information	
Package Level 1 Units	6 piece
Package Level 1 Width	88 mm
Package Level 1 Height	69.5 mm
Package Level 1 Depth / Length	222 mm
Package Level 1 Gross Weight	1.38 kg
Package Level 1 EAN	4013614519680
Package Level 2 EAN	4013614567032

Classifications	
Object Classification Code	Q
ETIM 5	EC001653 - Installation contactor for distribution board
ETIM 6	EC001653 - Installation contactor for distribution board
ETIM 7	EC001653 - Installation contactor for distribution board
eClass	V11.0 : 27142308
UNSPSC	39121529
IDEA Granular Category Code (IGCC)	4759 >> Installation contactor for distribution board
ETIM 8	EC001653 - Installation contactor for distribution board

Accessories				
Identifier	Description	Туре	Quantity	Unit Of Measure
1SAE901901R1011	EH04-11N Auxiliary Contact	EH04-11N	1	piece
1SAE901901M1011	EH04-11N Auxiliary Contact	EH04-11N	1	piece
1SAE901901R1020	EH04-20N Auxiliary Contact	EH04-20N	1	piece
1SAE901901M1020	EH04-20N Auxiliary Contact	EH04-20N	1	piece
GHE3201903R0001	ESB-PLK24 Sealing Cover	ESB-PLK24	1	piece
GHE3201902R0001	ESB-DIS Distance Piece	ESB-DIS	1	piece

Categories

 $Low\ Voltage\ Products\ and\ Systems\ \rightarrow\ Control\ Products\ \rightarrow\ Contactors\ \rightarrow\ Installation\ Contactors$ $Low\ Voltage\ Products\ and\ Systems\ \rightarrow\ Modular\ DIN\ Rail\ Products\ \rightarrow\ Command\ and\ Signalling\ Devices\ \rightarrow\ Installation\ Contactors$

